

## Beamz BT300

### DMX Chart

Channel	Function	Value	Description
1	Dimming	000 – 255	Master Dimming
2	Colour	000 – 009	No Function
		010 – 019	Red
		020 – 029	Green
		030 – 039	Blue
		040 – 049	White
		050 – 059	Amber
		060 – 069	UV
		070 – 079	Yellow
		080 – 089	Magenta
		090 – 099	Cyan
		100 – 109	Dark Orange
		110 – 119	Green Yellow
		120 – 121	Salmon
		130 – 139	Turquoise
		140 – 149	Light Green
		150 – 159	Orange
		160 -169	Lavender
		170 – 179	Light Blue
		180 – 189	Dark Blue
190 – 255	Pink		

Channel	Function	Value	Description
1	Colour	000 – 255	Red
2		000 - 255	Green
3		000 – 255	Blue

Channel	Function	Value	Description
1	Dimming	000 – 255	Master Dimming
2	Strobe	000 – 255	LED Strobe (slow – Fast)
3	Colour	000 – 009	No Function
		000 – 009	No Function
		010 – 019	Red
		020 – 029	Green
		030 – 039	Blue
		040 – 049	White
		050 – 059	Amber
		060 – 069	UV
		070 – 079	Yellow
		080 – 089	Magenta
		090 – 099	Cyan
		100 – 109	Dark Orange
		110 – 119	Green Yellow
		120 – 121	Salmon
		130 – 139	Turquoise
		140 – 149	Light Green
		150 – 159	Orange
		160 -169	Lavender
		170 – 179	Light Blue
180 – 189	Dark Blue		
190 – 255	Pink		
4	Auto / Sound	000 – 009	No Function
		010 – 069	Auto Colour Blending
		070 – 129	Auto Colour Change
		130 – 189	Sound Colour Blending
		190 – 255	Sound Colour Change

Channel	Function	Value	Description
1	Colour	000 – 255	Red 0% - 100%
2		000 – 255	Green 0% - 100%
3		000 – 255	Blue 0% - 100%
4		000 – 255	White 0% - 100%
5		000 – 255	Amber 0% - 100%
6		000 – 255	UV 0% - 100%